

Portable Radio Frequency Transmitter

Our lightweight Portable Radio Frequency Transmitter gives on-the-move transmission of clear speech to our portable receivers across 40 channels. It is supplied with a belt-clip to allow users to unobtrusively wear the unit when needed, and uses a micro-USB power supply to make charging the unit simple and fast.

Physical Data

Dimensions	Height – 85mm (3.34") Width – 50mm (1.96") Depth – 15mm (0.59")
Weight	66g (0.14lbs)
Finish	Grey

Technical Data

Lithium-Ion rechargeable battery 3.7V / 1100mAh (inbuilt)
Approx. 10 hours
2.4GHz (ISM band)
FSK, with hopping
150m in open air / 80m in buildings
40 simultaneous groups
50Hz – 7kHz
10mW
-95dBm
2Mbps
2 x 3.5mm 4 contact-socket
Micro-USB charge port

contacta | II.

RF-TX1

Applications

Ideal for situations where listeners require clear sound, tour guidance or interpretation:

- Museums
- Historical Sites
- Meeting Rooms
- Conferences
- Places of Worship

Components

- Portable Radio Frequency Transmitter
- Earworn Microphone
- Belt Clip
- USB Charger Cable
- Lanyard

Accessories

- 2 Bay Charging Station [RF-RX-CS2]
- 20 Bay Charger Case [RF-DC20]
- Microphone [RF-TX1-PM]
- Earworn Microphone [RF-TX1-EM]

Talk to us now: +44 (0) 1732 223900 (UK & ROW) +1 616 392 3400 (US & Canada) www.contacta.co.uk

